



(11) **EP 2 249 333 A1**

(12) **EUROPEAN PATENT APPLICATION**

(43) Date of publication: **10.11.2010 Bulletin 2010/45** (51) Int Cl.: **G10L 11/04 (2006.01)**

(21) Application number: **09006188.8**

(22) Date of filing: **06.05.2009**

(84) Designated Contracting States:
AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL PT RO SE SI SK TR
Designated Extension States:
AL BA RS

(71) Applicant: **Harman Becker Automotive Systems GmbH**
76307 Karlsbad (DE)

(72) Inventors:
• **Krini, Mohamed**
89073 Ulm (DE)
• **Schmidt, Gerhard**
89081 Ulm (DE)

(74) Representative: **Grünecker, Kinkeldey, Stockmair & Schwanhäusser**
Anwaltssozietät
Leopoldstrasse 4
80802 München (DE)

(54) **Method for estimating a fundamental frequency of a speech signal**

(57) The invention provides a method for estimating a fundamental frequency of a speech signal comprising the steps of receiving a signal spectrum of the speech signal, filtering the signal spectrum to obtain a refined signal spectrum, determining a cross-power spectral

density using the refined signal spectrum and the signal spectrum, transforming the cross-power spectral density into the time domain to obtain a cross-correlation function, and estimating the fundamental frequency of the speech signal based on the cross-correlation function.




FIG. 1

EP 2 249 333 A1

Description

[0001] The present invention relates to a method for estimating a fundamental frequency of a speech signal.

[0002] The spectrum of a voiced speech signal shows amplitude peaks which are equidistantly distributed in frequency space. The distance between two subsequent amplitude peaks corresponds to the fundamental frequency of the speech signal.

[0003] Estimating a fundamental frequency is an important issue of many applications relating to speech signal processing, for instance, for automatic speech recognition or speech synthesis. The fundamental frequency may be estimated, for example, for an impaired speech signal. Based on the fundamental frequency estimate, an undisturbed speech signal may be synthesized. In another example, the fundamental frequency estimate may be used to improve the recognition accuracy of a system for automatic speech recognition.

[0004] Several methods for estimating the fundamental frequency of a speech signal are known. One method, for example, is based on an harmonic product spectrum (see, e.g., M. R. Schroeder, "Period Histogram and Product Spectrum: New methods for fundamental frequency measurements", in Journal of the Acoustical Society of America, vol. 43, no. 4, 1968, pages 829 to 834).

[0005] Another class of methods is based on an analysis of the auto-correlation function of the speech signal (e.g. A. de Cheveigne, H. Kawahara, "Yin, a Fundamental Frequency Estimator for Speech and Music", JASA, 2002, 111 (4), pages 1917-1930). The auto-correlation function has a maximum at a lag associated with the fundamental frequency.

[0006] Methods based on the auto-correlation function, however, often encounter problems estimating low fundamental frequencies, as they can occur for male speakers. Methods to overcome this problem are hitherto either computationally inefficient or introduce a significant delay.

[0007] It is therefore the problem underlying the present invention to overcome the above-mentioned drawback and to provide an accurate method for estimating a fundamental frequency of a speech signal.

[0008] This problem is solved by a method according to claim 1.

[0009] According to the present invention, a method for estimating a fundamental frequency of a speech signal comprises the steps of:

receiving a signal spectrum of the speech signal;

filtering the signal spectrum to obtain a refined signal spectrum;

determining a cross-power spectral density using the refined signal spectrum and the signal spectrum;

transforming the cross-power spectral density into the time domain to obtain a cross-correlation function; and

estimating the fundamental frequency of the speech signal based on the cross-correlation function.

[0010] By determining a cross-correlation function between a signal spectrum and a refined or augmented signal spectrum, the amount of information in the cross-correlation function can be increased. In this way, the fundamental frequency of the speech signal can be estimated robustly and accurately, also for low fundamental frequencies.

[0011] The fundamental frequency may correspond to the lowest frequency component, lowest frequency partial or lowest frequency overtone of the speech signal. In particular, the fundamental frequency may correspond to the rate of vibrations of the vocal folds or vocal chords. The fundamental frequency may correspond to or be related to the pitch or pitch frequency. A speech signal may be periodic or quasi-periodic. In this case, the fundamental frequency may correspond to the inverse of the period of the speech signal, in particular wherein the period may correspond to the smallest positive time shift that leaves the speech signal invariant. A quasi-periodic speech signal may be periodic within one or more segments of the speech signal but not for the complete speech signal. In particular, a quasi-periodic speech signal may be periodic up to a small error.

[0012] The fundamental frequency may correspond to a distance in frequency space between amplitude peaks of the spectrum of the speech signal. The fundamental frequency depends on the speaker. In particular, the fundamental frequency of a male speaker may be lower than the fundamental frequency of a female speaker or of a child.

[0013] The signal spectrum may correspond to a frequency domain representation of the speech signal or of a part or segment of the speech signal. The signal spectrum may correspond to a Fourier transform of the speech signal, in particular, to a Fast Fourier Transform (FFT) or a short-time Fourier transform of the speech signal. In other words, the signal spectrum may correspond to an output of a short-time or short-term frequency analysis.

[0014] The signal spectrum may be a discrete spectrum, i.e. specified at predetermined frequency values or frequency nodes.

[0015] The signal spectrum of the speech signal may be received from a system or an apparatus used for speech

signal processing, for example, from a hands-free telephone set or a voice control, i.e. a voice command device. In this way, the efficiency of the method can be improved, as it uses input generated by another system.

5 [0016] The receiving step may be preceded by determining a signal spectrum of the speech signal. Determining a signal spectrum may comprise transforming the speech signal into the frequency domain. In particular, determining a signal spectrum may comprise processing the speech signal using a window function. Determining a signal spectrum may comprise performing a Fourier transform, in particular a discrete Fourier transform, in particular a Fast Fourier Transform or a short-time Fourier transform.

10 [0017] A refined signal spectrum may comprise an increased number of discrete frequency nodes compared to the signal spectrum. In other words, a refined signal spectrum may correspond to a frequency domain representation of the speech signal with an increased spectral resolution compared to the signal spectrum.

[0018] The signal spectrum and the refined signal spectrum may correspond to a predetermined sub-band or frequency band. In particular, the signal spectrum and the refined signal spectrum may correspond to sub-band spectra, in particular to sub-band short-time spectra.

15 [0019] By filtering the signal spectrum the method allows for a computationally efficient method to obtain a refined signal spectrum. In particular, filtering the signal spectrum may be computationally less expensive than determining a higher order Fourier transform of the speech signal to obtain a refined signal spectrum. Alternatively, however, a refined signal spectrum may be obtained by transforming the speech signal into the frequency domain, in particular using a Fourier transform.

20 [0020] Filtering the signal spectrum may be performed using a finite impulse response (FIR) filtering means. This guarantees a linear phase response and stability. Filtering the signal spectrum may be performed such that an algebraic mapping of the signal spectrum to a refined signal spectrum is realized. In particular, the step of filtering the signal spectrum may comprise combining the signal spectrum with one or more time delayed signal spectra, wherein a time delayed signal spectrum corresponds to a signal spectrum of the speech signal at a previous time.

25 [0021] Filtering the signal spectrum may comprise a time-delay filtering of the signal spectrum. The refined signal spectrum may correspond to a time delayed signal spectrum. In this case, the delay used for time-delay filtering of the signal spectrum may correspond to the group delay of the filtering means used for filtering the signal spectrum.

30 [0022] In the above-described methods the cross-power spectral density of the refined signal spectrum and the signal spectrum is determined. The step of determining the cross-power spectral density may comprise determining the complex conjugate of the refined signal spectrum or of the signal spectrum and determining a product of the complex conjugate of the refined signal spectrum and the signal spectrum or a product of the complex conjugate of the signal spectrum and the refined signal spectrum. The cross-power spectral density may be a complex valued function. The cross-power spectral density may correspond to the Fourier transform of a cross-correlation function.

[0023] The cross-power spectral density may be a discrete function, in particular specified at predetermined sampling points, i.e. for predetermined values of a frequency variable.

35 [0024] The step of transforming the cross-power spectral density into the time domain may be preceded by smoothing and/or normalizing the cross-power spectral density. In particular, the cross-power spectral density may be normalized based on a smoothed cross-power spectral density to obtain a normalized cross-power spectral density. In this way, the envelope of the cross-power spectral density may be cancelled.

40 [0025] Normalizing the cross-power spectral density may be based on an absolute value of the determined cross-power spectral density. In particular, the cross-power spectral density may be normalized using a smoothed cross-power spectral density, in particular, wherein the smoothed cross-power spectral density may be determined based on an absolute value of the cross-power spectral density.

45 [0026] The normalized cross-power spectral density may be weighted using a power spectral density weight function. In this way, predetermined frequency ranges may be associated with a higher statistical weight. In this way, the estimation of the fundamental frequency may be improved, as the fundamental frequency of a speech signal is usually found within a predetermined frequency range. For example, the power spectral density weight function may be chosen such that its value decreases with increasing frequency. In this way, the estimation of low fundamental frequencies may be improved.

50 [0027] Transforming the cross-power spectral density into the time domain may comprise an Inverse Fourier transform, in particular, an Inverse Fast Fourier transform. When using an Inverse Fast Fourier Transform, the required computing time may be further reduced. By transforming the cross-power spectral density into the time domain, a cross-correlation function can be obtained.

55 [0028] The cross-correlation function is a measure of the correlation between two functions, in particular between two wave fronts of the speech signal. In particular, the cross-correlation function is a measure of the correlation between two time dependent functions as a function of an offset or lag (e.g. a time-lag) applied to one of the functions.

[0029] The step of estimating the fundamental frequency may comprise determining a maximum of the cross-correlation function. In particular, estimating the fundamental frequency may comprise determining a maximum of the cross-correlation function in a predetermined range of lags. By determining a maximum of the cross-correlation function in a

predetermined range of lags, knowledge on a possible range of fundamental frequencies can be considered. In this way, the fundamental frequency can be estimated more efficiently, in particular faster, than when considering the complete available frequency space. The determined maximum may correspond to a local maximum, in particular, to the second highest maximum after the global maximum.

5 **[0030]** The step of estimating the fundamental frequency may further comprise compensating for a shift or delay of the cross-correlation function introduced by filtering the signal spectrum. Due to filtering of the signal spectrum, the cross-correlation function may have a maximum value at a lag corresponding to the group delay of the employed filter. The cross-correlation function may be corrected such that a signal with a predetermined period has a maximum in the cross-correlation function at a lag of zero and at lags which correspond to integer multiples of the period of the signal.
10 In this way, the cross-correlation function comprises similar properties as an auto-correlation function. In this way, estimating the fundamental frequency may be simplified.

[0031] In particular, in this case, the step of determining a maximum of the cross-correlation function may correspond to determining the highest non-zero lag peak of the cross-correlation function.

15 **[0032]** Estimating the fundamental frequency may comprise determining a lag of the cross-correlation function corresponding to the determined maximum of the cross-correlation function. This lag may correspond to or be proportional to the period of the speech signal. In particular, the fundamental frequency may be proportional to the inverse of the lag associated with the determined maximum of the cross-correlation function.

20 **[0033]** The speech signal may be a discrete or sampled speech signal. Estimating the fundamental frequency may be further based on the sampling rate of the sampled speech signal. In this way, the fundamental frequency may be expressed in physical units. In particular, the fundamental frequency may be estimated by determining the product of the sampling rate and the inverse of the lag associated with the determined maximum of the cross-correlation function. In this case, the lag may be dimensionless, in particular corresponding to a discrete lag variable of the cross-correlation function.

25 **[0034]** The step of estimating the fundamental frequency may comprise determining a weight function for the cross-correlation function. The weight function may be a discrete function. Similarly, the cross-correlation function may be a discrete function, which is specified for a predetermined number of sampling points. Each sampling point may correspond to a predetermined value of a lag variable. The weight function may be evaluated for the same number of sampling points, in particular for the same values of the lag variable, thereby obtaining a set of weights. The set of weights may form a weight vector. Each weight of the set of weights may correspond to a sampling point of the cross-correlation function. In other words, for each sampling point of the cross-correlation function a weight may be determined from the weight function.
30

[0035] Estimating the fundamental frequency may comprise weighting the cross-correlation function using the determined weight function or using the determined set of weights. In this way, the accuracy and/or the reliability of the fundamental frequency estimation may be further enhanced.

35 **[0036]** The weight function may comprise a bias term, a mean fundamental frequency term and/or a current fundamental frequency term.

[0037] The bias term may compensate for a bias of the estimation of the fundamental frequency. In particular, the bias term may compensate for a bias of the cross-correlation function. A bias may correspond to a difference between an estimated value of a parameter, for example, the fundamental frequency or a value of the cross-correlation function at a predetermined lag, and the true value of the parameter.
40

[0038] Determining a bias term of the weight function may be based on one or more cross-correlation functions of correlated white noise.

45 **[0039]** In particular, determining the bias term may comprise determining a cross-correlation function for each of a plurality of frames of correlated white noise, determining a time average of the cross-correlation functions, and determining the weight function based on the time average of the cross-correlation functions. In this way, a bias term compensating for a bias of the fundamental frequency estimation may be determined. In particular, the cross-correlation functions may be determined for Gaussian distributed white noise. The white noise may be correlated. The correlated white noise may be sub-band coded and/or short-time Fourier transformed, in particular, to obtain short time spectra of the white noise associated with the plurality of frames.

50 **[0040]** In particular, determining a cross-correlation function of correlated white noise may comprise receiving a spectrum of the correlated white noise, filtering the spectrum to obtain a refined spectrum, determining a cross-power spectral density of the spectrum and the refined spectrum, and transforming the cross-power spectral density into the time domain to obtain a cross-correlation function. In this way, the cross-correlation function may be determined in a similar way as the one obtained from the signal spectrum of the speech signal and the refined signal spectrum.

55 **[0041]** Determining a cross-correlation function may further comprise sampling the correlated white noise and filtering a short time spectrum associated with the correlated white noise, in particular using a predetermined frame shift.

[0042] Determining a time average of the cross-correlation functions may comprise averaging over cross-correlation functions determined for a plurality of frames of the correlated white noise. The number of frames used for determining

the time average may be determined based on a predetermined criterion. The predetermined criterion for the time average may be based on the predetermined frame shift and/or the sampling rate of the correlated white noise.

[0043] Determining the bias term based on the time average of the cross-correlation functions may comprise determining a minimum of a predetermined maximum value and the value of the time average of the cross-correlation functions at a given lag, in particular, normalized to the value of the time average of the cross-correlation at a lag of zero.

[0044] The speech signal may comprise a sequence of frames, and the signal spectrum may be a signal spectrum of a frame of the speech signal. In this way, a fundamental frequency can be estimated for a part of the speech signal. The sequence of frames may correspond to a consecutive sequence of frames, in particular, wherein frames from the sequence of frames are subsequent or adjacent in time.

[0045] Determining a mean fundamental frequency term of the weight function may be based on a mean fundamental frequency, in particular, on a mean lag associated with the mean fundamental frequency. In this way, predetermined values of the lag of the cross-correlation function may be favoured or enhanced.

[0046] In particular, the mean fundamental frequency term may be constant, in particular 1, for a predetermined range of lags comprising the mean lag. The predetermined range may be symmetric with respect to the mean lag. For lag values outside the predetermined range, the mean fundamental frequency term may take values smaller than for lag values inside the predetermined range. In particular, for lag values outside the predetermined range the mean fundamental frequency term of the weight function may decrease, in particular linearly. In this way, the cross-correlation function for values of the lag close to the mean lag, i.e. within the predetermined range, get a higher statistical weight. The mean fundamental frequency term may be bounded below. In this way, the mean fundamental frequency term cannot take values below a predetermined lower threshold. This may be particularly useful, if the mean fundamental frequency is a bad estimate for the fundamental frequency of the speech signal, in particular for the frame for which the fundamental frequency is being estimated.

[0047] Determining a current fundamental frequency term of the weight function may be based on a predetermined fundamental frequency, in particular, on a predetermined lag associated with the predetermined fundamental frequency. In this way, values of the lag close to the predetermined lag associated with a predetermined or current fundamental frequency may be associated with a higher statistical weight. The predetermined fundamental frequency may be, in particular, associated with a previous frame of the frame for which the fundamental frequency is being estimated. In particular, the previous frame may be the previous adjacent frame.

[0048] In particular, the current fundamental frequency term may be constant, in particular 1, for a predetermined range of lags comprising the predetermined lag. The predetermined range may be symmetric with respect to the predetermined lag. For lag values outside the predetermined range, the current fundamental frequency term may take values smaller than for lag values inside the predetermined range. In particular, for lag values outside the predetermined range the current fundamental frequency term of the weight function may decrease, in particular linearly. In this way, the cross-correlation function for values of the lag close to the predetermined lag, i.e. within the predetermined range, get a higher statistical weight. The current fundamental frequency term may be bounded below. In this way, the current fundamental frequency term cannot take values below a predetermined lower threshold. This may be particularly useful, if the predetermined fundamental frequency is a bad estimate for the fundamental frequency of the speech signal, in particular for the frame for which the fundamental frequency is being estimated.

[0049] Determining the weight function may comprise determining a combination, in particular a product, of at least two terms of the group of terms comprising a current fundamental frequency term, a mean fundamental frequency term and a bias term.

[0050] The step of estimating the fundamental frequency may comprise determining a confidence measure for the estimated fundamental frequency. In this way, the reliability of the estimation may be quantified. This may be particularly useful for applications using the estimate of the fundamental frequency, for example, methods for speech synthesis. Depending on the value of the confidence measure, such applications may adopt the fundamental frequency estimate or modify a fundamental frequency parameter according to a predetermined criterion.

[0051] The confidence measure may be determined based on the cross-correlation function, in particular, based on a normalized cross-correlation function. In particular, the confidence measure may correspond to the ratio of the value of the cross-correlation function, which has been compensated for a shift introduced by filtering the signal spectrum, at a lag associated with the determined maximum and a value of the cross-correlation function at a lag of zero. In this case, higher values of the confidence measure may indicate a more reliable estimate.

[0052] Filtering the signal spectrum may comprise augmenting the number of frequency nodes of the signal spectrum such that the number of frequency nodes of the refined signal spectrum is greater than the number of frequency nodes of the signal spectrum. Filtering may be performed using an FIR filter.

[0053] In particular, filtering the signal spectrum may comprise time-delay filtering the signal spectrum, in particular, using an FIR filter.

[0054] The speech signal may comprise a sequence of frames, and the steps of one of the above-described methods may be performed for the signal spectrum of each frame of the speech signal or for the signal spectrum of a plurality of

frames of the speech signal.

[0055] In particular, a method for estimating a fundamental frequency of a speech signal, wherein the speech signal comprises a sequence of frames, may comprise for each frame of the sequence of frames or for each frame of a plurality of frames:

- a receiving step for receiving a signal spectrum of the frame,
- a filtering step,
- a determining step for determining a cross-power spectral density,
- a transforming step for transforming the cross-power spectral density into the time domain, and
- an estimating step for estimating the fundamental frequency of the frame.

[0056] In this way, a temporary evolution of the fundamental frequency may be determined and/or the fundamental frequency may be estimated for a plurality of parts of the speech signal. This may be particularly relevant if the fundamental frequency shows variations in time. A frame may correspond to a part or a segment of the speech signal.

[0057] The sequence of frames may correspond to a consecutive sequence of frames, in particular, wherein frames from the sequence of frames are subsequent or adjacent in time.

[0058] Estimating the fundamental frequency of the speech signal may comprise averaging over the estimates of the fundamental frequency of individual frames of the speech signal, thereby obtaining a mean fundamental frequency.

[0059] The speech signal may comprise a sequence of frames for one or more sub-bands or frequency bands, and the steps of one of the above-described methods may be performed for the signal spectrum of a frame or of a plurality of frames of one or more sub-bands of the speech signal. For one or more predetermined sub-bands, the refined signal spectrum may correspond to a time delayed signal spectrum.

[0060] A signal spectrum for each frame may be determined using short-time Fourier transforms of the speech signal. For this purpose, the speech signal is multiplied with a window function and the Fourier transform is determined for the window.

[0061] A frame or a window of the speech signal may be obtained by applying a window function to the speech signal. In particular, a sequence of frames may be obtained by processing the speech signal using a plurality of window functions, wherein the window functions are shifted with respect to each other in time. The shift between each pair of window functions may be constant. In this way, frames equidistantly spaced in time may be obtained.

[0062] The invention may provide a method for setting a fundamental frequency value or fundamental frequency parameter, wherein the fundamental frequency of a speech signal is estimated as described above, and wherein a fundamental frequency parameter is set to the estimated fundamental frequency if a confidence measure exceeds a predetermined threshold. In particular, the fundamental frequency parameter may be set to the mean fundamental frequency. Otherwise, if the confidence measure does not exceed the predetermined threshold, the fundamental frequency value may be set to a preset value or set to a value indicating a non-detectable fundamental frequency.

[0063] The invention further provides a computer program product, comprising one or more computer-readable media, having computer executable instructions for performing the steps of one of the above-described methods, when run on a computer.

[0064] The invention further provides an apparatus for estimating a fundamental frequency of a speech signal according to one of the above-described methods, comprising:

- receiving means configured to receive a signal spectrum of the speech signal,
- filtering means configured to filter the signal spectrum to obtain a refined signal spectrum,
- determining means configured to determine a cross-power spectral density using the refined signal spectrum and the signal spectrum,
- transforming means configured to transform the cross-power spectral density into the time domain to obtain a cross-correlation function and
- estimating means configured to estimate the fundamental frequency of the speech signal based on the cross-correlation function.

[0065] The invention further provides a system, in particular, a hands-free system, comprising an apparatus as described above. In particular, the hands-free system may be a hands-free telephone set or a hands-free speech control system, in particular, for use in a vehicle.

[0066] The system may comprise a speech signal processing means configured to perform noise reduction, echo cancelling, speech synthesis or speech recognition. In particular, the system may comprise transformation means configured to transform the speech signal into one or more signal spectra. In particular, the transformation means may comprise Fast Fourier transformation means for performing a Fast Fourier Transform or a short-time Fourier transformation means for performing a short-time Fourier Transform.

[0067] Additional features and advantages of the present invention will be described with reference to the drawings. In the description, reference is made to accompanying Figures that are meant to illustrate preferred embodiments of the invention.

Fig. 1: illustrates a method for estimating a fundamental frequency of a speech signal;

Fig. 2 illustrates a method for estimating a weight function;

Fig. 3 illustrates a method for estimating a fundamental frequency;

Fig. 4 illustrates a method for estimating a fundamental frequency based on an auto-power spectral density of a refined signal spectrum;

Fig. 5 shows an example for an application of a fundamental frequency estimation;

Fig. 6 shows an example for an application of a fundamental frequency estimation;

Fig. 7 shows a spectrogram of a speech signal;

Fig. 8 shows a spectrogram and an analysis of an auto-correlation function;

Fig. 9 shows a spectrogram and an analysis of an auto-correlation function based on a refined signal spectrum; and

Fig. 10 shows a spectrogram and an analysis of a cross-correlation function based on a refined signal spectrum and a signal spectrum.

[0068] The spectrum of a voiced speech signal or of a segment of the voiced speech signal, may comprise amplitude peaks equidistantly distributed in frequency space. Fig. 7 shows a spectrogram, i.e. a time-frequency analysis, of a speech signal. The x-axis shows the time in seconds and the y-axis shows the frequency in Hz. In this Figure the difference in frequency between two amplitude peaks corresponds to the fundamental frequency of the speech signal. The amplitude peaks 731 correspond to frequency partials or frequency overtones of the speech signal. In particular, the fundamental frequency 730 is shown as the lowest frequency partial or lowest frequency overtone of the speech signal. The value of the fundamental frequency or pitch frequency depends on the speaker. For men, the fundamental frequency usually varies between 80 Hz and 150 Hz. For women and children, the fundamental frequency varies between 150 Hz and 300 Hz for women and between 200 Hz and 600 Hz for children, respectively. Especially, the detection of low fundamental frequencies, as they can occur for male speakers, can be difficult.

[0069] An estimation of the fundamental frequency of a speech signal can be necessary in many different applications. Fig. 6 shows an example for an application of a method for estimating a fundamental frequency. In particular, Fig. 6 shows a system for speech synthesis, in particular, for reconstructing an undisturbed speech signal (see e.g. "Model-based Speech Enhancement" by M. Krini and G. Schmidt, in E. Hänsler, G. Schmidt (eds.), Topics in Speech and Audio Processing in Adverse Environments, Berlin, Springer, 2008). For such an application, it is often required to provide a reliable estimate of the fundamental frequency which does not introduce a signal delay. Additionally, a computationally efficient method may be required, as the fundamental frequency should be estimated in real time.

[0070] In particular, Fig. 6 shows filtering means 616 for converting an impaired speech signal, $y(n)$, into sub-band short-time spectra, $Y(e^{j\Omega_\mu}, n)$. Here and in the following the parameter n denotes a time variable, in particular a discrete time variable. A fundamental frequency estimating apparatus 617 yields an estimate of the fundamental frequency of the impaired speech signal. Further features of the speech signal may be extracted by feature extraction means 620. The speech synthesis means 621 uses the information obtained from the fundamental frequency estimating apparatus 617 and the feature extraction means 620 to determine a synthesized short-time spectrum, $X(e^{j\Omega_\mu}, n)$. Filtering means 622 converts the synthesized short-time spectrum into an undisturbed output signal, $x(n)$.

[0071] Another system using a fundamental frequency estimating apparatus is shown in Fig. 5. In particular, Fig. 5 shows a system for automatic speech recognition. For this purpose, a transformation means 516 transforms a speech signal, $y(n)$, into short-time spectra, $Y(e^{j\Omega_\mu}n)$. A fundamental frequency estimating apparatus 517 is used to estimate the fundamental frequency, $f_p(n)$. Further features of the speech signal are extracted by feature extracting means 518. Speech recognition means 519 yield a speech recognition result based on the estimated fundamental frequency and the features estimated by the feature estimating means 518. A reliable and/or robust estimation of the fundamental frequency can yield an improvement of the speech recognition system, in particular of the speech recognition accuracy.

[0072] Several methods are known for estimating a fundamental frequency of a speech signal. One method comprises determining a product of the absolute value of the frequency spectrum at equidistant sampling points. This method is termed Harmonic Product Spectrum Method (see e.g. M. R. Schroeder, "Period Histogram and Product Spectrum: New Method for Fundamental Frequency Measurements", J. Acoust. Soc. Am., 1968, Vol. 43, Nr. 4, pages 829-834).

[0073] An alternative method is based on modelling speech generation as a source-filter model. In particular, a fundamental frequency of the speech signal can be estimated in the Cepstral-domain.

[0074] Another method for estimating a fundamental frequency is based on a short-time auto-correlation function (see, e.g. A. de Cheveigne, H. Kawahara, "Yin, a Fundamental Frequency Estimator for Speech and Music", JASA, 2002, pages 1917-1930).

[0075] In the following, it is assumed that a speech signal is detected using at least one microphone. The speech signal, $s(n)$, is often superimposed by a noise signal, $b(n)$. A microphone signal, $y(n)$, hence, may be composed of speech and noise, e.g.

$$y(n) = s(n) + b(n).$$

[0076] From the microphone signal, a short-time auto-correlation function in the time domain may be determined as follows:

$$\hat{r}_{yy}(m, n) = \frac{1}{L} \sum_{k=0}^{L-1} y(n-k)y(n-k+m).$$

[0077] Here m denotes the lag of the auto-correlation function. A direct estimation of the auto-correlation function from the microphone signal, however, may be time consuming. Therefore, an estimate for a correlation function may be determined based on a signal spectrum, in particular, a short-time signal spectrum. One or more signal spectra may be received from a multi-rate system for speech signal processing, i.e. from a system using two or more sampling frequencies for processing a speech signal. One sampling frequency may be used for under-sampling of the speech signal. Determining a signal spectrum may be based on a predetermined sampling frequency, in particular on the sampling frequency used for under-sampling.

[0078] The receiving step may be preceded by determining a signal spectrum. In particular, a speech signal may be sub-divided and/or windowed, in particular, to obtain overlapping frames of the speech signal (see, e.g. E. Hänsler, G. Schmidt, "Acoustic Echo and Noise Control - A Practical Approach", John Wiley & Sons, New Jersey, USA, 2004). A frame may correspond to a signal input vector. Depending on the order, N , used for the discrete Fourier Transform, a signal input vector of a frame of the speech signal may read:

$$\vec{y}(n) = [y(n), y(n-1), \dots, y(n-N+1)]^T.$$

[0079] The upper index T denotes the transposition operation. Each signal input vector may be weighted using a window function, h :

$$\vec{h} = [h_0, h_1, \dots, h_{N-1}]^T.$$

5
[0080] Using a discrete Fourier Transform, the weighted signal input vector may be transformed into the frequency domain, i.e.

$$10 \quad Y(e^{j\Omega_\mu}, n) = \sum_{k=0}^{N-1} y(n-k)h_k e^{-j\Omega_\mu k}.$$

15 **[0081]** The frequency nodes or frequency sampling points, Ω_μ , may be equidistantly distributed in the frequency domain, i.e.:

$$20 \quad \Omega_\mu = \frac{2\pi}{N} \mu \quad \text{where } \mu \in \{0, \dots, N-1\}.$$

[0082] Fig. 3 illustrates a method for estimating a fundamental frequency. From the signal spectrum, a power spectral density may be determined:

$$25 \quad \hat{S}_{yy}(\Omega_\mu, n) = |Y(e^{j\Omega_\mu}, n)|^2 = Y(e^{j\Omega_\mu}, n)Y^*(e^{j\Omega_\mu}, n).$$

30 Here $Y^*(e^{j\Omega_\mu}, n)$ denotes the complex conjugate of the signal spectrum, which may be determined by complex conjugate means 311.

[0083] The power spectral density may be smoothed in the frequency domain and subsequently divided by the envelope of the power spectral density obtained by smoothing. In this way, the envelope may be removed from the power spectral density. Smoothing the power spectral density may read:

$$40 \quad \tilde{S}_{yy}(\Omega_\mu, n) = \begin{cases} \hat{S}_{yy}(\Omega_\mu, n) & \text{for } \mu = 0, \\ \lambda \tilde{S}_{yy}(\Omega_{\mu-1}, n) + (1-\lambda)\hat{S}_{yy}(\Omega_\mu, n) & \text{for } \mu \in \{1, \dots, N-1\} \end{cases},$$

and

$$50 \quad \bar{S}_{yy}(\Omega_\mu, n) = \begin{cases} \tilde{S}_{yy}(\Omega_\mu, n) & \text{for } \mu = N-1, \\ \lambda \bar{S}_{yy}(\Omega_{\mu+1}, n) + (1-\lambda)\tilde{S}_{yy}(\Omega_\mu, n) & \text{for } \mu \in \{0, \dots, N-2\} \end{cases}.$$

[0084] A smoothing constant λ may be chosen from a predetermined range. The smoothed and normalized power spectral density may be weighted using a power spectral density weight function, W :

55

$$\hat{S}_{yy,norm}(\Omega_\mu, n) = \frac{\hat{S}_{yy}(\Omega_\mu, n)}{\bar{S}_{yy}(\Omega_\mu, n)} W(e^{j\Omega_\mu}).$$

5

[0085] Smoothing and weighting the power spectral density may be performed by normalizing means 312.

[0086] By transforming the power spectral density into the time domain, in particular using inverse transformation means 313, an auto-correlation function may be obtained, i.e.

10

$$\hat{r}_{yy}(m, n) = \frac{1}{N} \sum_{\mu=0}^{N-1} \hat{S}_{yy,norm}(\Omega_\mu, n) e^{j\frac{2\pi}{N}\mu m}.$$

15

[0087] From the auto-correlation function, a fundamental frequency of the speech signal may be estimated using estimating means 314.

[0088] Fig. 8 shows a spectrogram and an analysis of the auto-correlation function of a speech signal. In this case, the auto-correlation function was determined using a method, as described above in context of Fig. 3. The x-axis shows the time in seconds and the y-axis shows the frequency in Hz in the lower panel and the lag in number of sampling points in the upper panel, respectively. The white solid lines in the lower panel of Fig. 8 indicate estimates of the fundamental frequency 830 and its harmonics 831, in particular wherein the difference between two subsequent or adjacent white lines corresponds to the (time-dependent) fundamental frequency of the speech signal. The black solid line 832 in the upper panel indicates the lag of the auto-correlation function corresponding to the estimated fundamental frequency.

20

25

[0089] The speech signal corresponds to a combination, in particular a superposition, of 10 sinusoidal signals with equal amplitude. The frequencies of the sinusoidal signals were chosen equidistantly in the frequency domain. In particular, initially a fundamental frequency of 300 Hz was chosen, which was decreased linearly with time down to a frequency of 60 Hz. The order of the discrete Fourier Transform used in this example was $N = 256$, the sampling frequency of the speech signal was 11025 Hz and the auto-correlation function was analyzed in a lag range between $m = 40$ and $m = 128$. It can be seen that a fundamental frequency down to 120 Hz can be estimated using this method, while lower fundamental frequencies (below 120 Hz) could not be reliably estimated.

30

35

[0090] In Fig. 4, another method for estimating a fundamental frequency of a speech signal is illustrated. The method illustrated in Fig. 4 differs from the method of Fig. 3 in that the signal spectrum is spectrally refined before calculating the power spectral density. In other words, an auto-power spectral density is calculated from a refined signal spectrum. The spectral refinement may be performed using refinement means 415. The spectral refinement, however, can introduce a significant signal delay in the signal path. Complex conjugate means 411 may determine a complex conjugate of a refined signal spectrum. Smoothing and weighting of the auto-power spectral density may be performed by normalizing means 412. By transforming the auto-power spectral density into the time domain, in particular using inverse transformation means 413, an auto-correlation function may be obtained. From the auto-correlation function, a fundamental frequency of the speech signal may be estimated using estimating means 414.

40

45

[0091] Fig. 9 shows an analysis of the auto-correlation function based on a refined signal spectrum, as described in context of Fig. 4, in the upper panel, and a spectrogram of the signal spectrum in the lower panel. The x-axis shows the time in seconds and the y-axis shows the frequency in Hz in the lower panel and the lag in number of sampling points in the upper panel, respectively. The parameters underlying the speech signal used for this analysis were chosen as described above in context of Fig. 8. For the spectral refinement, a frame shift of $r = 64$ was used. It can be seen that the fundamental frequency can be reliably estimated up to a shift of $m = 128$, which corresponds, in this example, to a fundamental frequency of 90 Hz. For lower frequencies, however, the estimate of the fundamental frequency 930, as indicated by the lowest of the white lines, differs from the true fundamental frequency which continues to decrease to lower frequencies down to 60 Hz. Furthermore, Fig. 9 shows harmonics 931 of the fundamental frequency. The black solid line 932 in the upper panel indicates the lag of the auto-correlation function corresponding to the estimated fundamental frequency.

50

55

[0092] In Fig. 1, a method for estimating a fundamental frequency of a speech signal is illustrated. In this case, a cross-power spectral density is estimated or determined based on a signal spectrum, $Y(e^{j\Omega_\mu}, n)$, and a refined signal spectrum, $\tilde{Y}(e^{j\Omega_\mu}, n)$, wherein the refined signal spectrum corresponds to a spectrally refined or augmented signal spectrum. The parameter μ denotes here the μ -th sampling point of the signal spectrum and of the refined signal spectrum. However, the number of frequency nodes of the refined signal spectrum is higher than the number of frequency nodes

of the signal spectrum. The cross-power spectral density may be calculated as:

$$\begin{aligned} \hat{S}_{y\tilde{y}}(\Omega_\mu, n) &= Y(e^{j\Omega_\mu}, n) \tilde{Y}^*(e^{j\Omega_\mu}, n) \\ &= Y(e^{j\Omega_\mu}, n) \left[\sum_{m'=0}^{M-1} g_{\mu, m'} Y(e^{j\Omega_\mu}, n - m') \right]^* \end{aligned}$$

[0093] Here, $g_{\mu, m'}$ denote the FIR filter coefficients of a sub-band. A set of filter coefficients may read:

$$\mathbf{g}_\mu = [g_{\mu, 0}, g_{\mu, 1}, \dots, g_{\mu, M-1}]^T.$$

[0094] The filter order of the FIR filter is denoted by the parameter M which may take a value in the range between 3 and 5. For a predetermined sub-band, a refined signal spectrum may be written as:

$$\tilde{Y}(e^{j\Omega_\mu}, n) = g_{\mu, 0} Y(e^{j\Omega_\mu}, n) + \dots + g_{\mu, M-1} Y(e^{j\Omega_\mu}, n - (M-1)r).$$

[0095] Here the parameter r denotes a frame shift. In particular, time delayed signal spectra, $Y(e^{j\Omega_\mu}, n - m'r)$, may be obtained by time delay filtering of the signal spectrum, with $m' \in \{0, M-1\}$. Details on the filtering procedure, in particular on the choice of the filter coefficients, can be found in "Spectral refinement and its Application to Fundamental Frequency Estimation", by M. Krini and G. Schmidt, Proc. IEEE WASPAA, Mohonk, New York, 2007.

[0096] The filtering may be performed by filtering means 101. From the refined signal spectrum the complex conjugate may be determined, in particular using complex conjugate means 102.

[0097] By determining a cross-power spectral density of the refined signal spectrum and the signal spectrum following differences compared to the determination of an auto-power spectral density of a refined signal spectrum may occur. First of all, no additional delay is inserted into the signal path. The cross-correlation function estimated based on the cross-power spectral density may have a maximum value at the group delay of the employed filter. For a phase linear

filter, the lag corresponding to the group delay may correspond to $\frac{M-1}{2}r$ sampling points. In other words, a maximum

expected for an auto-correlation function at a lag of zero, may be shifted for the cross-correlation function to a lag corresponding to the group delay of the filter used for filtering the signal spectrum.

[0098] Furthermore, a cross-power spectral density is usually a complex valued function. In contrast to this, an auto-power spectral density is usually a real valued function. Therefore, compared to prior art methods, the amount of available information may be doubled using the cross-power spectral density. Therefore, even if filtering the signal spectrum comprises only a time-delay filtering of the signal spectrum, the estimation of the fundamental frequency can be improved by increasing, for example, doubling, the amount of available information. The cross-power spectral density may be symmetric to $\Omega = \pi$.

[0099] The cross-power spectral density may be normalized and weighted with a predetermined cross-power spectral density weight function, $W(e^{j\Omega_\mu})$. In particular, the normalization may be determined based on the absolute value of the determined cross-power spectral density, i.e.

$$\hat{S}_{y\tilde{y}, norm}(\Omega_\mu, n) = \frac{\hat{S}_{y\tilde{y}}(\Omega_\mu, n)}{\hat{S}_{y\tilde{y}}(\Omega_\mu, n)} W(e^{j\Omega_\mu}),$$

with

$$\bar{S}_{y\bar{y}}(\Omega_\mu, n) = \begin{cases} \tilde{S}_{y\bar{y}}(\Omega_\mu, n) & \text{for } \mu = N-1 \\ \lambda \bar{S}_{y\bar{y}}(\Omega_{\mu+1}, n) + (1-\lambda)\tilde{S}_{y\bar{y}}(\Omega_\mu, n) & \text{for } \mu \in \{0, \dots, N-2\} \end{cases}$$

and

$$\tilde{S}_{y\bar{y}}(\Omega_\mu, n) = \begin{cases} |\hat{S}_{y\bar{y}}(\Omega_\mu, n)| & \text{for } \mu = 0, \\ \lambda \tilde{S}_{y\bar{y}}(\Omega_{\mu-1}, n) + (1-\lambda)|\hat{S}_{y\bar{y}}(\Omega_\mu, n)| & \text{for } \mu \in \{1, \dots, N-1\}. \end{cases}$$

[0100] The smoothing constant λ may be chosen from a predetermined interval, in particular, between 0.3 and 0.7. The weighting and normalizing may be performed using the cross-power spectral density weighting means 103.

[0101] The cross-power spectral density may be transformed into the time domain as

$$\hat{r}_{y\bar{y},pre}(m, n) = \frac{1}{N} \sum_{\mu=0}^{N-1} \hat{S}_{y\bar{y},norm}(\Omega_\mu, n) e^{j\frac{2\pi}{N}\mu m},$$

thereby obtaining an estimate for a cross-correlation function. The Inverse Discrete Fourier Transform may be implemented as Inverse Fast Fourier Transform, in order to improve the computational efficiency. The transformation may be performed by inverse transformation means 104.

[0102] The cross-correlation function may be determined for a predetermined number of sampling points, which correspond to a predetermined number of discrete values of the lag variable, m . For example, if an inverse Fast Fourier Transform is used for transforming the cross-power spectral density into the time domain, the predetermined number may correspond to the order of the Fourier Transform.

[0103] In order to compensate for a delay or shift introduced by filtering the signal spectrum into the cross-correlation function, the cross-correlation function may be modified as:

$$\hat{r}_{y\bar{y}}(m, n) = \hat{r}_{y\bar{y},pre}((m + R) \bmod N, n).$$

[0104] The parameter R denotes the shift, in particular, in form of a number of sampling points associated with the shift or delay, introduced by filtering the signal spectrum. The expression "mod" denotes the modulo operation. After this correction, the value of the cross-correlation function at a lag of zero corresponds to a maximum and the cross-correlation function of a periodic signal with a period P may have local maxima at integer multiples of P . In other words, after compensating for the delay, the cross-correlation function may have similar properties as an auto-correlation function. This modification may be performed by the inverse transformation means 104.

[0105] Subsequently, the cross-correlation function may be weighted using a set of weights, $w(n)$, with

$$w(n) = [w(0, n), \dots, w(m, n), \dots, w(N-1, n)]^T,$$

and the weighted cross-correlation function may be normalized to its value at a lag of zero, i.e.

$$\hat{r}_{y\bar{y},\text{mod}}(m,n) = \frac{\hat{r}_{y\bar{y}}(m,n)w(m,n)}{\hat{r}_{y\bar{y}}(0,n)}.$$

5

[0106] The weighting may be performed by weighting means 107. The weighting means 107 may use a fundamental frequency estimate from a previous frame, in particular from a previous adjacent frame. Delay means 106 may be used for delaying a fundamental frequency estimate, $\hat{f}_p(n)$, and/or a confidence measure, $\hat{\rho}_{f_p}(n)$, e.g. by one frame.

10 **[0107]** The weights from the set of weights may correspond to discrete values of a weight function, $w(m,n)$, evaluated for sampling points m of the cross-correlation function. The weight function may comprise a bias term compensating for a bias of the estimation of the fundamental frequency, in particular, wherein the bias term is time independent, and a time dependent term. In particular, the weight function may be a combination, in particular a product, of a bias term and a time dependent term, i.e.

15

$$\overline{w(m,n)} = w_b(m)w_p(m,n).$$

20 **[0108]** Fig. 2 illustrates a method for estimating a bias term of the weight function. White noise, in particular, Gaussian distributed white noise may be correlated using correlation means 208 and transformed into the frequency domain by transformation means 209. Correlating the white noise may comprise a time-delay filtering of the white noise. A cross-correlation function may be determined for each of a plurality of frames of the correlated white noise as described above for the signal spectrum and the refined signal spectrum. In particular, a signal spectrum of the correlated white noise
25 may be filtered by filtering means 201 and complex conjugated using complex conjugate means 202. A determined cross-power spectral density may be normalized and weighted using cross-power spectral density weighting means 203. Inverse transformation means 204 may be used to transform the determined cross-power spectral density into the time domain thereby obtaining a cross-correlation function.

30 **[0109]** A time average over the cross-correlation functions may be determined as

35

$$\overline{\hat{r}_{y\bar{y}}(m)} = \frac{1}{N_{av}} \sum_{n=0}^{N_{av}-1} \hat{r}_{y\bar{y}}(m,n).$$

[0110] The parameter N_{av} may define the number of frames for which the time average is calculated. The parameter N_{av} may be determined as

40

$$N_{av} = \left\lceil \frac{3 \text{ seconds } f_s}{r} \right\rceil,$$

45

where f_s denoted the sampling frequency of the correlated white noise and r denotes the frame shift introduced by the filtering step. The operator $\lceil \cdot \rceil$ denotes a round-up operator configured to round its argument up to the next higher integer.

[0111] The bias term of the weight function may be determined, in particular using a weight function determining means 210, as

50

$$w_b(m) = \min \left\{ w_{\max}, \frac{\overline{\hat{r}_{y\bar{y}}(m)}}{\overline{\hat{r}_{y\bar{y}}(0)}} \right\},$$

55

where w_{\max} denotes a maximum compensation value, which, for example, may take a value of $w_{\max} = 2$.

[0112] A time variable weight function or time variable term of a weight function may be a product or a combination of two terms or factors:

$$w_p(m, n) = w_{p,mean}(m, n)w_{p,curr}(m, n)$$

[0113] A mean fundamental frequency term, $w_{p,mean}(m, n)$, may be based on an average fundamental frequency and a current fundamental frequency term, $w_{p,curr}(m, n)$, may be based on a predetermined fundamental frequency estimate of a previous, in particular adjacent previous, frame.

[0114] The mean fundamental frequency term, $w_{p,mean}(m, n)$, of the weight function based on an average fundamental frequency of previous frames may be determined as

$$w_{p,mean}(m, n) = \begin{cases} \max\{w_{p,min}, w_{p,mean}(m+1, n)b_{mean}\} & \text{for } m < 0.8\overline{\tau_p(n-1)} \\ 1 & \text{for } 0.8\overline{\tau_p(n-1)} \leq m \leq 1.2\overline{\tau_p(n-1)} \\ \max\{w_{p,min}, w_{p,mean}(m-1, n)b_{mean}\} & \text{otherwise} \end{cases}$$

[0115] Here, the parameter b_{mean} determines the decrease, in particular the linear decrease, of the weight function outside a range of lag values comprising the lag associated with the mean fundamental frequency. In particular, the parameter b_{mean} may be constant and may be determined from a range between 0.9 and 0.98. A predetermined lower boundary value $w_{p,min}$ may be chosen to be 0.3.

[0116] The period associated with a fundamental frequency at a given time, i.e. for a predetermined frame n , may be estimated, in particular using estimating means 105, as

$$\tau_p(n) = \arg \max_{m_1 \leq m \leq m_2} \{\hat{r}_{y\bar{y},mod}(m, n)\}.$$

[0117] Here m_1 and m_2 denote the lower and upper boundary values, respectively, of a lag range in which a maximum of the cross-correlation function is searched. For instance, m_1 may take a value of 30 and m_2 may take a value of 180, which may correspond to approximately 367 Hz and 60 Hz, respectively, for a predetermined sampling frequency of 11025 Hz.

[0118] The mean period, $\overline{\tau_p(n)}$, associated with a mean fundamental frequency at time n , may be estimated as

$$\overline{\tau_p(n)} = \begin{cases} \beta_\tau \overline{\tau_p(n-1)} + (1 - \beta_\tau)\tau_p(n) & \text{if } \frac{\hat{r}_{y\bar{y}}(\tau_p(n), n)w_b(\tau_p(n))}{\hat{r}_{y\bar{y}}(0, n)} > s_0 \\ \overline{\tau_p(n-1)} & \text{otherwise.} \end{cases}$$

[0119] Here, the mean period associated with the mean fundamental frequency is only modified if a confidence criterion is fulfilled, i.e. if

$$\frac{\hat{r}_{y\bar{y}}(\tau_p(n), n)w_b(\tau_p(n))}{\hat{r}_{y\bar{y}}(0, n)} > s_0,$$

where s_0 denotes a threshold, in particular, wherein the threshold may be chosen from the interval between 0.4 and 0.5.
[0120] The current fundamental frequency term of the weight function based on a predetermined fundamental frequency estimate, in particular the fundamental frequency estimate of the previous, adjacent frame, may be determined as:

$$w_{p,curr}(m, n) = \begin{cases} \max\{w_{p,min}, w_{p,curr}(m+1, n)b_{curr}\} & \text{for } m < 0.8\tau_p(n-1) \\ 1 & \text{for } 0.8\tau_p(n-1) \leq m \leq 1.2\tau_p(n-1) \\ \max\{w_{p,min}, w_{p,curr}(m-1, n)b_{curr}\} & \text{otherwise} \end{cases}$$

[0121] Here, the parameter b_{curr} determines the decrease, in particular the linear decrease, of the weight function outside a predetermined range of lag values comprising the lag associated with the predetermined fundamental frequency estimate. In particular, the parameter b_{curr} may be constant and may be determined from a range between 0.95 and 0.995.
[0122] If no reliable estimate of the fundamental frequency was possible for the previous frame, i.e. if

$$\frac{\hat{r}_{y\bar{y}}(\tau_p(n-1), n-1)\omega_b(\tau_p(n-1))}{\hat{r}_{y\bar{y}}(0, n-1)} < s_0$$

the current fundamental frequency term may be set to 1, i.e.

$$w_{p,curr}(m, n) = 1.$$

[0123] From the period, $\tau_p(n)$, at a given time n , i.e. for a frame corresponding to the time n , the fundamental frequency may be estimated as:

$$f'_p(n) = \frac{f_s}{\tau_p(n)},$$

where f_s denotes the sampling frequency of the speech signal.

[0124] A confidence measure may be determined as

$$\hat{p}_{f_p}(n) = \frac{\hat{r}_{y\bar{y}}(\tau_p(n), n)\omega_b(\tau_p(n))}{\hat{r}_{y\bar{y}}(0, n)}.$$

[0125] Alternatively, the confidence measure may read

$$\hat{p}_{f_p}(n) = \frac{\hat{r}_{y\bar{y}}(\tau_p(n), n)}{\hat{r}_{y\bar{y}}(0, n)}.$$

[0126] A higher value of the confidence measure may indicate a more reliable estimate.

[0127] A fundamental frequency parameter, f_p , e.g. of a speech synthesis apparatus, may be set to the estimated fundamental frequency if the confidence measure exceeds a predetermined threshold. The predetermined threshold may be chosen between 0.2 and 0.5, in particular, between 0.2 and 0.3. For example, setting the fundamental frequency parameter may read:

$$f_p(n) = \begin{cases} f'_p(n) & \text{if } \hat{p}_{f_p}(n) > p_0 \\ F_p & \text{else.} \end{cases}$$

[0128] Here F_p denotes a preset fundamental frequency value or a parameter indicating that the fundamental frequency may not be reliably estimated.

[0129] Fig. 10 shows a spectrogram and an analysis of a cross-correlation function based on a refined signal spectrum and a signal spectrum, as described in context of Fig. 1. The x-axis shows the time in seconds and the y-axis shows the frequency in Hz in the lower panel and the lag in number of sampling points in the upper panel, respectively. The parameters underlying the speech signal used for this analysis were chosen as described above in the context of Figs. 8 and 9. For the spectral refinement, a frame shift of $r = 64$ was used. It can be seen that the fundamental frequency can be well estimated, in particular also at low fundamental frequencies. Again the lowest white line 1030 indicates the estimate of the fundamental frequency and the black solid line 1032 indicates the corresponding lag of the cross-correlation function. Furthermore the harmonics 1031 of the fundamental frequency are shown in the lower panel.

[0130] Although previously discussed embodiments have been described separately, it is to be understood that some or all of the above-described features can also be combined in different ways. Discussed embodiments are not intended as limitations but serve as examples illustrating features and advantages of the invention.

Claims

1. A method for estimating a fundamental frequency of a speech signal comprising the steps of:

receiving a signal spectrum of the speech signal;
 filtering the signal spectrum to obtain a refined signal spectrum;
 determining a cross-power spectral density using the refined signal spectrum and the signal spectrum;
 transforming the cross-power spectral density into the time domain to obtain a cross-correlation function; and
 estimating the fundamental frequency of the speech signal based on the cross-correlation function.

2. The method according to claim 1, wherein estimating the fundamental frequency comprises determining a maximum of the cross-correlation function.

3. The method according to claim 2, wherein estimating the fundamental frequency comprises determining a lag of the cross-correlation function corresponding to the determined maximum of the cross-correlation function.

4. The method according to any one of the preceding claims, wherein the step of estimating the fundamental frequency comprises determining a weight function for the cross-correlation function and weighting the cross-correlation function with the determined weight function.

5. The method according to claim 4, wherein the weight function comprises a bias term, wherein the bias term compensates for a bias of the estimation of the fundamental frequency.

6. The method according to claim 5, wherein determining the bias term of the weight function is based on one or more cross-correlation functions of correlated white noise.

7. The method according to any one of the preceding claims, wherein the speech signal comprises a sequence of frames, and wherein the signal spectrum is a signal spectrum of a frame of the speech signal.

8. The method according to claim 7, wherein the weight function comprises a mean fundamental frequency term and/or a current fundamental frequency term, wherein determining the mean fundamental frequency term is based on a mean fundamental frequency, and/or wherein determining the current fundamental frequency term is based on a

predetermined fundamental frequency, in particular, wherein the predetermined fundamental frequency corresponds to a fundamental frequency estimate of a previous frame of the speech signal.

5 9. The method according to claim 7 or 8, wherein determining the weight function comprises determining a combination, in particular a product, of at least two terms of the group of terms comprising a current fundamental frequency term, a mean fundamental frequency term and a bias term.

10 10. The method according to any one of the previous claims, wherein the step of estimating the fundamental frequency comprises compensating the cross-correlation function for a shift or delay introduced by filtering the signal spectrum.

11. The method according to any one of the preceding claims, wherein the step of estimating the fundamental frequency comprises determining a confidence measure for the estimated fundamental frequency.

15 12. The method according to any one of the preceding claims, wherein filtering the signal spectrum comprises augmenting the number of frequency nodes of the signal spectrum such that the number of frequency nodes of the refined signal spectrum is greater than the number of frequency nodes of the signal spectrum.

20 13. The method according to any one of the preceding claims, wherein the speech signal comprises a sequence of frames, and wherein the steps of the method are performed for the signal spectrum of each frame of the speech signal or for the signal spectrum of a plurality of frames of the speech signal.

14. Computer program product, comprising one or more computer readable media having computer-executable instructions for performing the steps of the method according to one of the previous claims, when run on a computer.

25 15. An apparatus for estimating a fundamental frequency of a speech signal, according to the method of one of the claims 1 - 13, comprising:

receiving means configured to receive a signal spectrum of the speech signal;
30 filtering means 101 configured to filter the signal spectrum to obtain a refined signal spectrum;
determining means configured to determine a cross-power spectral density using the refined signal spectrum and the signal spectrum;
transforming means 104 configured to transform the cross-power spectral density into the time domain to obtain a cross-correlation function; and
35 estimating means 105 configured to estimate the fundamental frequency of the speech signal based on the cross-correlation function.

16. A system for speech signal processing comprising:

40 transformation means configured to transform the speech signal into one or more signal spectra;
an apparatus according to claim 15 for estimating a fundamental frequency.

45

50

55




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8





FIG. 9




FIG. 10



EUROPEAN SEARCH REPORT

Application Number
EP 09 00 6188

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
X	<p>MOHAMED KRINI ET AL: "Spectral Refinement and its Application to Fundamental Frequency Estimation" APPLICATIONS OF SIGNAL PROCESSING TO AUDIO AND ACOUSTICS, 2007 IEEE WO RKSHP ON, IEEE, PI, 1 October 2007 (2007-10-01), pages 251-254, XP031167113 ISBN: 978-1-4244-1618-9 * abstract * * page 251, right-hand column, paragraph 2 - page 252, left-hand column, paragraph 2 * * page 252, par. [2.2. Realization of Spectral Refinement] * * page 253, par. [3. APPLICATIONS OF SPECTRAL REFINEMENT] * * page 253, par. [3.2. Enhanced Fundamental Frequency Estimation] * -----</p>	1-4,7, 10-16	INV. G10L11/04
A	<p>EP 1 944 754 A (HARMAN BECKER AUTOMOTIVE SYS [DE]) 16 July 2008 (2008-07-16) * abstract * * page 3, par. [0015] * * figures 2-4 * ----- -/--</p>	1-16	<p>TECHNICAL FIELDS SEARCHED (IPC)</p> <p>G10L</p>
The present search report has been drawn up for all claims			
Place of search Munich		Date of completion of the search 16 September 2009	Examiner Greiser, Norbert
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p>		<p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>	

2
EPO FORM 1503 03 82 (P04C01)



EUROPEAN SEARCH REPORT

Application Number
EP 09 00 6188

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (IPC)
A	<p>QUAST H ET AL: "Robust pitch tracking in the car environment" 2002 IEEE INTERNATIONAL CONFERENCE ON ACOUSTICS, SPEECH, AND SIGNAL PROCESSING. PROCEEDINGS. (ICASSP). ORLANDO, FL, MAY 13 - 17, 2002; [IEEE INTERNATIONAL CONFERENCE ON ACOUSTICS, SPEECH, AND SIGNAL PROCESSING (ICASSP)], NEW YORK, NY : IEEE, US, vol. 1, 13 May 2002 (2002-05-13), pages 1-353, XP010804765 ISBN: 978-0-7803-7402-7 * abstract * * page 353, par. [2. PITCH TRACKING ALGORITHMS] *</p> <p style="text-align: center;">-----</p>	1,14-16	
			TECHNICAL FIELDS SEARCHED (IPC)
The present search report has been drawn up for all claims			
Place of search Munich		Date of completion of the search 16 September 2009	Examiner Greiser, Norbert
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

2
EPO FORM 1503 03.02 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 09 00 6188

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

16-09-2009

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 1944754	A	16-07-2008	NONE

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Non-patent literature cited in the description

- **M. R. Schroeder.** Period Histogram and Product Spectrum: New methods for fundamental frequency measurements. *Journal of the Acoustical Society of America*, 1968, vol. 43 (4), 829-834 [0004]
- **A. de Cheveigne ; H. Kawahara.** Yin, a Fundamental Frequency Estimator for Speech and Music. *JASA*, 2002, vol. 111, 1917-1930 [0005]
- **Model-based Speech Enhancement.** Topics in Speech and Audio Processing in Adverse Environments. Springer, 2008 [0069]
- **M. R. Schroeder.** Period Histogram and Product Spectrum: New Method for Fundamental Frequency Measurements. *J. Acoust. Soc. Am.*, 1968, vol. 43 (4), 829-834 [0072]
- **A. de Cheveigne ; H. Kawahara.** Yin, a Fundamental Frequency Estimator for Speech and Music. *JASA*, 2002, 1917-1930 [0074]
- **E. Hänsler ; G. Schmidt.** Acoustic Echo and Noise Control - A Practical Approach. John Wiley & Sons, 2004 [0078]
- **M. Krini ; G. Schmidt.** Spectral refinement and its Application to Fundamental Frequency Estimation. *Proc. IEEE WASPAA*, 2007 [0095]